



LIQUID LEAK DETECTION SYSTEMS

FG-A Alarm Unit

Product Datasheet



- ▶ Analogue Leak Detection System
- ▶ Simple Detection Without Location
- ▶ Three LED Indicators
- ▶ Two Output Relays
- ▶ Adjustable Sensitivity

Description

The FG-A alarm unit is designed to be used with TTK analogue sense cables (FG-ECS, FG-ECX, FG-ACS, FG-ACX) to give immediate detection of liquid leaks (water, acid or base).

LED's on the front of the panel indicate the presence of Power Supply (green), Leak Detected (red) or Cable Break (yellow).

Responses on the FG-A alarm unit:

- In the case of a leak an audible alarm is triggered. The red LED is switched on and the leak relay is activated.
- In the case of cable break an audible alarm is triggered, the yellow LED is switched on and the cable break relay is activated.

The "SOUND OFF" button on the front of the panel allows manual silencing of the audible alarm. The LED's and corresponding relays remain activated as long as the fault persists. When the fault is corrected the LED's and relays return to normal status.

Features & Benefits

FEATURES

- Available as a wall mounted unit.
- The unit can control sense cables up to 15 metres.
- Visual and audible indicators for the type of fault (leak or cable break).
- Flexible supply voltage: 12-24VAC ;15-30VDC or 100-240VAC 50/60Hz.
- Easily accessible terminals for rapid installation.
- Two zero volt contact relays provide numerous signalling and centralised monitoring options.

BENEFITS

- The FG-A is simple and easy to use, making an ideal choice for small or remote applications.
- Detects cable break faults.
- The sensitivity of the unit is adjustable via the potentiometer on the PCB.
- A simple bi-annual test is all that is required.

Technical Data

Compatibility	Analogue sense cables: FG-ECS, FG-ECX, FG-ACS, FG-ACX
Enclosure Type	ABS material (rated to UL94HB)
Operating Temperature	0°C to 50°C
Relays Type: Leak + Cable Break	1 SPDT single contact NO-NC
Dry Relay Max. Switching Voltage	125VAC or 220VDC
Relay Max. Switching Capacity	60W (30V x 2A)
Power Consumption	2VA
Supply Voltage	12-24VAC, 15-30 VDC or 100-240VAC - 50/60Hz
Dimensions (W,H,D)	172 x 86.6 x 55 mm

Panel Description

- 1: The leak signal (red LED) indicates that the system has detected a liquid leak.
- 2: The continuity signal (yellow LED) indicates that the system has detected a circuit interruption.
- 3: The power supply signal (green LED) indicates that the system is in normal operation.
- 4: The button is used to stop the audible alarm.



Dimensions



FG-A Wall Mounted Unit

Electrical Information

Power Supply	N : Neutral / P : Phase / : Earth
Cable Break Relay	R1 : NO / R2 : COM / R3 : NC
Leak Relay	R1 : NO / R2 : COM / R3 : NC
FG-CLC Leader Cable	A : Green wire / B : White wire / C : Black wire / D : Red wire

Identification Codes

FG-A	Alarm unit FG-A wall mounted
Accessories:	
FG-CLC	Leader cable of 3.5 metres length
FG-ECS, FG-ACS and FG-ECX, FG-ACX	Water or acids sensing cable in 3m, 7m, and 15m in length
FG-TMX	End termination plug
CF-EC100	100 hold-down clips with adhesive
ES-40	40 tags

Certificates



The FG-A unit meets the requirements of all European Standards in EN 50081 and EN 50082 EMC.

All the connections in the FG-A alarm unit must be done with the power supply switched off. Read carefully the installation procedure for the FG-A alarm unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this project. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.

FG-SYS, FG-NET and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2024

- **TTK Headquarters** / 19, rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / www.ttk.fr / ventes@ttk.fr
- **TTK UK Ltd.** / 3 Luke Street / London EC2A 4PX / United Kingdom / T : +44 207 729 6002 / F : +44 207 729 6003 / www.ttkuk.com / sales@ttkuk.com
- **TTK Pte Ltd.** / #09-05, Shenton House, 3 Shenton Way / Singapore 068805 / T: +65.6220.2068 / M: +65.9271.6191 / F: +65-6220.2026 / www.ttk.sg / sales@ttk.sg
- **TTK Asia Ltd.** / 2107-2108 Kai Tak Commercial Building / 317 Des Voeux Road Central / Hongkong / T: +852.2858.7128 / F: +852.2858.8428 / www.ttkasia.com / info@ttkasia.com
- **TTK Middle East FZCO** / Building 6EA, Office 510 PO Box 54925 / Dubai Airport Free Zone / UAE / T: +971 4 70 17 553 / M: +971 50 259 66 29 / www.ttkuk.com / cgalmiche@ttk.fr
- **TTK Deutschland GmbH** / Berner Strasse 34 / 60437 Frankfurt / Deutschland / T : +49(0)69-95005630 / F : +49(0)69-95005640 / www.ttk-gmbh.de / vertrieb@ttk-gmbh.de
- **TTK North America Inc** / 1900 City Park Drive, 3rd Floor / Ottawa, ON K1J 1G7 / Canada / T : +1 613 566 5968 / www.ttkcanada.com / info@ttkcanada.com
- **TTK USA Inc.** / 100 S. Broad Street, Suite 730 / Philadelphia, PA 19110 / Tel. +1 610 304 2270 / www.ttkusa.com / bmcnevin@ttkusa.com